Data sheet for three-phase Squirrel-Cage-Motors SIMOTICS



Motor type : 1AV4132B SIMOTICS GP - 132 M - IM B5 - 4p Offer no. Client order no. Item-No Order no. Consignment no. Project Remarks Safe Area **Electrical data** -/η 3) Δ/Υ U f Р Р ī М cosφ ³⁾ I_A/I_N M_A/M_N M_K/M_N IE-CL n [V] [Hz] [kW] [hp] [A] [1/min] [Nm] 4/4 3/4 T_I/T_N T_B/T_N 2/4 4/4 3/4 2/4 I_I/I_N **DOL duty (S1)** - 155(F) to 130(B) 230 Δ 50 7.50 25.00 1470 48.5 92.6 93.1 92.7 0.81 0.75 0.64 7.7 3.0 4.0 IE4 400 7.50 -/-14.40 0.75 4.0 50 1470 48.5 92.6 93.1 92.7 0.81 0.64 7.7 3.0 IE4 Υ 60 8.60 -/-14.20 1770 46.5 92.4 92.8 92.4 0.77 0.67 7.9 2.9 3.9 IE4 460 0.82 Υ -/-IE4 460 60 7.50 1775 40.5 92.4 92.5 91.8 0.80 0.74 0.63 8.8 3.4 4.5 12.70 IM B5 / IM 3001 UKCA IEC/EN 60034 IEC, DIN, ISO, VDE, EN FS 132 M Environmental conditions: -20 °C - +40 °C / 1000 m Locked rotor time (hot / cold): 27.5 s | 36.5 s Mechanical data Sound level (SPL / SWL) at 50Hz|60Hz 56 / 68 dB(A) 2) 3) 61 / 73 dB(A) 2) 3) Vibration severity grade Α Moment of inertia 0.0460 kg m² Thermal class F Bearing DE | NDE 6208 2Z C3 6208 2Z C3 Duty type S1 bearing lifetime Direction of rotation bidirectional $L_{10mh}\,F_{Rad\,\,min}$ for coupling operation $50|60Hz^{\,1)}$ 40000 h 32000 h Frame material aluminum Regreasing device Without Net weight of the motor (IM B3) 62 kg Coating (paint finish) Standard paint finish C2 Grease nipple Preloaded bearing DE RAL7030 Type of bearing Color, paint shade Condensate drainage holes Without Motor protection (B) 3 PTC thermistors - for tripping (2 terminals) IC416 - separately ventilated, surface cooled External earthing terminal Without Method of cooling Terminal box Terminal box position top Max. cross-sectional area 6 mm^2 Material of terminal box Aluminium Cable diameter from ... to ... 11 mm - 21 mm Type of terminal box TB1 H00 2xM32x1,5-1xM16x1,5 Cable entry Contact screw thread Μ4 Cable gland 3 plugs 1) L_{10mh} according to DIN ISO 281 10/2010 3) Value is valid only for DOL operation with motor design IC411 IA/IN = locked rotor current / current nominal M_A/M_N = locked rotor torque / torque nominal 2) at rated power / at full load M_K/M_N = break down torque / nominal torque Transmittal, reproduction, dissemination and/or editing of this document as well as utilization of its contents and communication thereof to others without express authorization are prohibited. Offenders will be held liable for payment of damages. All rights created by patent grant or registration of a utility model or design patent are reserved Responsible department Technical reference Created by Approved by Technical data are subject to change! There may be discrepancies between calculated and rating plate IN LVM SPC Created automatically Document type Document status Released Technical data sheet **SIEMENS** Document number

TDS-240417-162044

Creation date

2024-04-17

Language

Page

Revision

© Innomotics 2024

Restricted

1LE1004-1CB22-2FB4-Z

F01+F11+F50+F70

Data sheet for three-phase Squirrel-Cage-Motors SIMOTICS



	rpe:1AV4132B		SIMOT	ICS GP - 132 M - IN	/I В5 - 4р		
Special c				_			
F01	Mounting of holding			F50		manual brake release with lever (ca	nnot be locked)
F11	Brake supply voltage, 230 V AC, 50/60 Hz			F70 Mount		nting of separately driven fan	
Additio	nal information:						
Brake:							
Description	on:	BFK458-16		Current		.27 A	
Voltage:		AC 230 V		Women	nt of inertia:	0.001500 kgm	
	reproduction, dissemination and/o rights created by patent grant or re			nts and communication thereo	f to others without exp	press authorization are prohibited. Offenders will	be held liable for payment of
	e department	Technical reference	Created by	Approved by	discrep	ical data are subject to change! There may be pancies between calculated and rating plate	Link documents
IN LVM		Document type	SFC.	Created autor	matically values	Document status	
	EMENS	Technical data sheet				Released	
SII	EIVI EIVS	Document title 1LE1004-1CB22-2FB4-Z				Document number TDS-240417-162044	

Revision

Creation date

2024-04-17

Language

Page 2/2

© Innomotics 2024

Restricted

F01+F11+F50+F70