## **SIEMENS**

## **Data sheet**

## 6ES7143-5AH00-0BA0



SIMATIC ET 200AL, DIQ 16x24 V DC/0.5 A, 8xM12, Degree of protection IP67

General information	
Product type designation	DIQ 16x24VDC/0.5A
HW functional status	FS03
Firmware version	V1.2.x
Product function	
● I&M data	Yes; I&M0 to I&M3
Engineering with	
<ul> <li>STEP 7 TIA Portal configurable/integrated from version</li> </ul>	STEP 7 V14 or higher
<ul> <li>STEP 7 configurable/integrated from version</li> </ul>	V5.5 SP4 Hotfix 7 or higher
<ul> <li>PROFIBUS from GSD version/GSD revision</li> </ul>	GSD as of Revision 5
<ul> <li>PROFINET from GSD version/GSD revision</li> </ul>	GSDML V2.3.1
Operating mode	
• DI	Yes
Counter	Yes
• DQ	Yes
Supply voltage	
power supply according to NEC Class 2 required	No
Load voltage 1L+	
<ul><li>Rated value (DC)</li></ul>	24 V
<ul> <li>permissible range, lower limit (DC)</li> </ul>	20.4 V
<ul> <li>permissible range, upper limit (DC)</li> </ul>	28.8 V
Reverse polarity protection	Yes; Against destruction; encoder power supply outputs applied with reversed polarity, loads pick up
Load voltage 2L+	
<ul><li>Rated value (DC)</li></ul>	24 V
<ul> <li>permissible range, lower limit (DC)</li> </ul>	20.4 V
<ul> <li>permissible range, upper limit (DC)</li> </ul>	28.8 V
Reverse polarity protection	Yes; Against destruction; encoder power supply outputs applied with reversed polarity, loads pick up
Input current	
Current consumption (rated value)	75 mA; without load
from load voltage 1L+ (unswitched voltage)	4 A; Maximum value
from load voltage 2L+, max.	4 A; Maximum value
Encoder supply	
Number of outputs	8
24 V encoder supply	
Short-circuit protection	Yes; Per load voltage, electronic
Output current, max.	1.4 A; Total current of all encoders, max. 0.7 A per load voltage
Power loss	
Power loss, typ.	4 W

Digital inputs	
Number of digital inputs	16; Parameterizable as DIQ
Input characteristic curve in accordance with IEC 61131, type 3	Yes
Number of simultaneously controllable inputs	
all mounting positions	
— up to 55 °C, max.	16
Digital input functions, parameterizable	
Freely usable digital input	Yes
Counter	Yes
— Number, max.	4
<ul> <li>Counting frequency, max.</li> </ul>	2 kHz
— Counting width	32 bit; Incl. sign
— Counting direction up/down	Yes
Input voltage	
Rated value (DC)	24 V
• for signal "0"	-3 to +5V
• for signal "1"	+11 to +30V
Input current	
● for signal "1", typ.	3 mA
Input delay (for rated value of input voltage)	
for standard inputs	
— parameterizable	Yes
— at "0" to "1", min.	0.05 ms; 1.6 ms for channels 8 through 15
— at "0" to "1", max.	20 ms
— at "1" to "0", min.	0.05 ms; 1.6 ms for channels 8 through 15
— at "1" to "0", max.	20 ms
for technological functions	
— parameterizable	Yes
Cable length	
• unshielded, max.	30 m
Digital outputs	
Number of digital outputs	16; Parameterizable as DIQ
• in groups of	8; 2 load groups for 8 outputs each
Short-circuit protection	Yes; per channel, electronic
Response threshold, typ.	0.7 A
Limitation of inductive shutdown voltage to	0.7 A L+ (-53 V)
Limitation of inductive shutdown voltage to Digital output functions, parameterizable	L+ (-53 V)
Limitation of inductive shutdown voltage to Digital output functions, parameterizable  • Switching tripped by comparison values	L+ (-53 V) Yes
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  • Switching tripped by comparison values  • Freely usable digital output	L+ (-53 V)
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  • Switching tripped by comparison values  • Freely usable digital output  Switching capacity of the outputs	L+ (-53 V) Yes Yes
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  • Switching tripped by comparison values  • Freely usable digital output  Switching capacity of the outputs  • on lamp load, max.	L+ (-53 V) Yes
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  • Switching tripped by comparison values  • Freely usable digital output  Switching capacity of the outputs  • on lamp load, max.  Load resistance range	L+ (-53 V) Yes Yes 5 W
Limitation of inductive shutdown voltage to Digital output functions, parameterizable  • Switching tripped by comparison values  • Freely usable digital output Switching capacity of the outputs  • on lamp load, max. Load resistance range  • lower limit	L+ (-53 V)  Yes  Yes  5 W  48 Ω
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  • Switching tripped by comparison values  • Freely usable digital output  Switching capacity of the outputs  • on lamp load, max.  Load resistance range  • lower limit  • upper limit	L+ (-53 V) Yes Yes 5 W
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage	L+ (-53 V)  Yes  Yes  5 W  48 Ω  4 kΩ
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.	L+ (-53 V)  Yes  Yes  5 W  48 Ω
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current	L+ (-53 V)  Yes  Yes  5 W  48 Ω  4 kΩ  L+ (-0.8 V)
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "1" rated value	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.	L+ (-53 V)  Yes  Yes  5 W  48 Ω  4 kΩ  L+ (-0.8 V)
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "1" rated value  for signal "0" residual current, max.  Switching frequency	L+ (-53 V)  Yes  Yes  5 W  48 Ω  4 kΩ  L+ (-0.8 V)  0.5 A  0.5 mA
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.	L+ (-53 V)  Yes  Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "1" rated value  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA  100 Hz 0.5 Hz
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.  on lamp load, max.	L+ (-53 V)  Yes  Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.  on lamp load, max.  Total current of the outputs	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA  100 Hz 0.5 Hz
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.  on lamp load, max.  Current per group, max.	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA  100 Hz 0.5 Hz 1 Hz
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.  on lamp load, max.  Cable length	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA  100 Hz 0.5 Hz 1 Hz
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.  on lamp load, max.  Total current of the outputs  Current per group, max.  Cable length  unshielded, max.	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA  100 Hz 0.5 Hz 1 Hz
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.  on lamp load, max.  Cable length	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA  100 Hz 0.5 Hz 1 Hz
Limitation of inductive shutdown voltage to  Digital output functions, parameterizable  Switching tripped by comparison values  Freely usable digital output  Switching capacity of the outputs  on lamp load, max.  Load resistance range  lower limit  upper limit  Output voltage  for signal "1", min.  Output current  for signal "0" residual current, max.  Switching frequency  with resistive load, max.  with inductive load, max.  on lamp load, max.  Total current of the outputs  Current per group, max.  Cable length  unshielded, max.  Encoder	L+ (-53 V)  Yes Yes  5 W  48 Ω 4 kΩ  L+ (-0.8 V)  0.5 A 0.5 mA  100 Hz 0.5 Hz 1 Hz

— permissible quiescent current (2-wire sensor), max.	1.5 mA
Interrupts/diagnostics/status information	
Substitute values connectable	Yes; channel by channel, parameterizable
Alarms	
Diagnostic alarm	Yes; Parameterizable
Diagnoses	
Short-circuit	Yes; Outputs to M; encoder supply to M; module by module
Diagnostics indication LED	
Channel status display	Yes; green LED
<ul> <li>for module diagnostics</li> </ul>	Yes; green/red LED
<ul> <li>For load voltage monitoring</li> </ul>	Yes; green LED
Potential separation	
between the load voltages	Yes
Potential separation channels	
<ul> <li>between the channels, in groups of</li> </ul>	8
<ul> <li>between the channels and backplane bus</li> </ul>	Yes
<ul> <li>between the channels and the power supply of the electronics</li> </ul>	No; 8 channels are non-isolated and 8 channels are isolated from supply voltage 1L+
Isolation	
Isolation tested with	707 V DC (type test)
Degree and class of protection	
IP degree of protection	IP65/67
Ambient conditions	
Ambient temperature during operation	
• min.	-30 °C
• max.	55 °C
connection method	
Design of electrical connection for the inputs and outputs	M12, 5-pole
Design of electrical connection for supply voltage	M8, 4-pole
ET-Connection ET-Connection	
• ET-Connection	M8, 4-pin, shielded
Dimensions	
Width	45 mm
Height	159 mm
Depth	40 mm
Weights	
Weight, approx.	195 g

last modified:

5/22/2024