



EJ1008 | 8-channel digital input 24 V DC, 3 ms

The EJ1008 digital input acquires the binary control signals from the process level and transmits them, in an electrically isolated form, to the higher-level automation unit. The digital inputs have a 3 ms input filter. The EtherCAT plug-in modules indicate their state via an LED.

Technical data	EJ1008
Specification	EN 61131-2, type 1/3
Number of inputs	8
Nominal voltage	24 V DC (-15 %/+20 %)
"0" signal voltage	-3...+5 V (EN 61131-2, type 1/3)
"1" signal voltage	11...30 V (EN 61131-2, type 3)
Input current	typ. 3 mA (EN 61131-2, type 3)
Input filter	typ. 3.0 ms
Distributed clocks	–
Current consumption E-bus	typ. 80 mA
Electrical isolation	500 V (E-bus/field potential)
Bit width in the process image	8 inputs
Special features	standard input module for bouncing signals (filter 3 ms)
Dimensions (W x H x D)	approx. 12 mm x 66 mm x 55 mm
Operating/storage temperature	0...+55 °C/-25...+85 °C
Relative humidity	95 %, no condensation
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protection class	IP 20
Approvals	CE