

ISOLATION TRANSFORMER;
 PHASES:1;
 PN(KVA):0,025;
 UPRI(V):400+/-5%;
 USEC(V):42;
 ISEC(A):0,595;
 F(HZ):50...60;
 VECTOR GR./SHIELD WNG.:li0 /0;
 TA/ISOKL:40 /B;
 IP00;
 TYPE OF TERMINALS:SCREW/TAB CONNECTION;
 INSTALLATION:SCREW;
 EN 61558-2-1,
 -2-4 >UL/CSA-RECOGNIZED< >ISOLATION
 TRANSFORMER<

General technical details:

Product designation		transformer SITAS
product brand name		SIDAC
Operating apparent output / rated value	V·A	25
Efficiency		0.74
Manner of switching for transformers		li0
Verification of suitability		CE / cRUus
Product function		
• temperature surveillance		No
• isolation control		No
• short circuit and overload protection		No
Number of the protective coils		0
Relative short-circuit voltage	%	17.6

Inputs:

Phase number / of the inputs		1
Input voltage		
• _1 / rated value	V	420
• _2 / rated value	V	400
• _3 / rated value	V	380
Electrical input frequency		
• minimum	Hz	50
• maximum	Hz	60

Outputs:

Phase number / of the outputs		1
Output voltage		
• _1 / rated value	V	24
Electrical output frequency		
• maximum	Hz	60
• minimum	Hz	50

Ambient conditions:

Thermal class / according to IEC 60085		B
Ambient temperature / rated value	°C	40
Protection class IP		IP00

Mechanical design:

Design of the electrical connection		
• secondary side / for main current circuit		screw-type terminals / tab terminals
• at the input / for main current circuit		screw-type terminals / tab terminals
Mounting type		screws
Construction form of the iron core		EI 60/20
Width	m	0.062
Height	m	0.079
Depth	m	0.078

Certificates/approvals:

General Product Approval

Shipping Approval

other

[other](#)**Further information:****Information- and Downloadcenter (Catalogs, Brochures,...)**<http://www.siemens.com/industrial-controls/catalogs>**Industry Mall (Online ordering system)**<http://www.siemens.com/industrial-controls/mall>**CAX-Online-Generator**<http://www.siemens.com/cax>**Service&Support (Manuals, Certificates, Characteristics, FAQs,...)**<http://support.automation.siemens.com/WWW/view/en/4AM2342-5AV00-0EA0/all>**Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)**http://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=4AM2342-5AV00-0EA0**last change:**

Dec 5, 2011